

It is important to note that as many raster points as possible are wanted for error-tolerant and at the same time efficient coding. The number of raster points is, however, limited by the total length of the bit stream. This should not of course be lengthened as a result of rastering, since there would then be unused places in the bit stream, something which would contradict the philosophy of overall data compression. However, it must also be pointed out that a lengthening of the bit stream may well be accepted in the interests of a high degree of error tolerance in certain applications. Another point to be considered is that a raster should preferably be structured so that as many code words as possible start on raster points. The present invention thus permits effective flexibility in the choice of raster point distance as compared with the prior art. In the absolutely ideal case this flexibility would lead to each code word having a raster point assigned to it, something which involves considerable technical effort. The method of arranging the raster points, i.e. determining the distance between the raster points of each spectral section according to the relevant code table, permits a very close approximation to the optimal case, however, especially since not all the code words are psychoacoustically significant and since all the psychoacoustically less significant code words can be slotted into the bit stream between the rastered psychoacous-

According to a third aspect of the present invention the code words are no longer arranged in the bit stream in a linearly increasing sequence as regards frequency but the code words for different spectral values are "scrambled". In Fig. 1 it can be seen that there is to a certain extent an interleaved linear arrangement of the code words with frequency since the hatched priority code words are arranged in order of increasing frequency and the non-priority code words, which are not hatched, are also slotted into the bit stream in order of increasing frequency. If a so-called "burst" error were now to occur in the bit stream shown in Fig. 1, i.e. a disturbance which leads to the corruption of a number of successive code words, the code words 6, 7a, 2, 3 and 7b for example could be affected simultaneously.

In the corresponding decoded audio signal a disturbance which is spectrally relatively wide and thus likely to be distinctly audible would occur in the spectral band represented by the priority code words 2 and 3. The problem of burst errors is not very apparent from the very simple example in Fig. 1. In practice, however, it can be assumed that there will be many more than 5 raster points and that burst errors will often extend over a plurality of raster points, which can lead to a loss of data for a relatively wide frequency band. It is for this reason that, according to the third aspect of the present invention, the priority code words of the spectral values are preferably no longer arranged in ascending order as to frequency but are "mixed up" in such a way as to have a random or pseudo-random arrangement as regards frequency. The non-priority code words may also optionally be treated in the same way. In the case of a pseudo-random arrangement it is not necessary to transmit any information on the distribution as side

information since this distribution can be set in the decoder a priori. As a consequence the loss of successive code words in the bit stream would not lead to the loss of a complete frequency band but simply to a very small loss in several frequency bands. This disturbance would scarcely be audible and could also be concealed more efficiently than the loss of a complete frequency band.

According to a fourth aspect of the present invention, instead of an arrangement of the priority and non-priority code words which increases linearly with the frequency an arrangement can also be used in which e.g. only each n-th code word is arranged in the raster and the remaining code words are slotted between them. As has already been stated, the number of raster points for a bit stream is limited by the total length and the distance between the raster points. If e.g. sampling with low bandwidth is considered, the case can occur that the vast majority of the code words are psychoacoustically significant code words since the whole signal has a theoretically possible useful bandwidth of 8 kHz if a sampling rate of 16 kHz is used. Experience shows that only 30% of the code words can be arranged on raster points, the other 70% being required to fill up the raster completely. This would mean, however, that the important frequency range, the range 0 - 4 kHz for speech signals e.g., cannot be covered or "protected" with priority code words arranged on raster points. To achieve adequate protection against error propagation for the important frequency range, therefore, instead of aligning every priority code word with a raster point this is done only for every second, third, fourth, etc. priority code word, while the other priority code words fill up the raster without being aligned. If e.g. every second or every third etc. spectral value is known in the low frequency range and the interspersed code words are corrupted during transmission, it may be possible to reconstitute these

00000001.000001